



Product Documentation

Imprivata MAM Reference Architecture: Hardware Requirements

Imprivata Mobile Access Management
Q2 2025

Contacting Imprivata

20 CityPoint, 480 Totten Pond Road, 6th Floor

Waltham, MA 02451 USA

Phone: 781-674-2700

Toll-Free: 1-877-OneSign

Fax: 1 781 674 2760

Support: 1 800 935 5958 (North America)

Support: 001 408-987-6072 (Outside North America)

<https://www.imprivata.com>

support@imprivata.com

Copyright and Legal Information

© 2025 Imprivata, Inc. All Rights Reserved.

This product is distributed under licenses restricting its use, copying, distribution and decompilation.

Imprivata's products may be covered in whole or in part by one or more U.S. pending or issued patents listed at <http://www.imprivata.com/patents>.

Trademark Information

OneSign, Imprivata, and the Imprivata logo are registered trademarks of Imprivata, Inc. ProveID and Imprivata OneSign APG are trademarks of Imprivata, Inc. in the United States and in other countries.

Legal Notices

Under international copyright laws, neither the documentation nor software may be copied, photocopied, reproduced, translated, or reduced to any electronic medium or machine-readable form, in whole or in part without the prior written consent of Imprivata, Inc., except as described in the license agreement.

The names of companies, products, people, and/or data mentioned herein are fictitious and are in no way intended to represent any real individual, company, product, or event, unless otherwise noted.

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.

Document revision Q2 2025

Imprivata Mobile Access Management Reference Architecture: Hardware Requirements

This reference architecture provides the hardware and software configurations tested and qualified by Imprivata for use with the Imprivata Mobile Access Management (MAM) solution.

This guide is designed to help new customers make purchasing decisions by providing a list of Imprivata supported devices, operating systems, and connectivity options for optimal performance and compatibility. These configurations have been rigorously tested with the goal of seamless integration and functionality, minimizing potential issues for a smooth user experience.



NOTE:

While Imprivata strongly recommends using the supported configurations, we are committed to providing the highest level of support possible and upon request, will assist in troubleshooting and resolution of issues for other setups, where feasible.

			Apple Devices with Lightning Port	Apple Devices with USB-C Port	Android Devices
Mobile Device		Device Model	iPhone 14 iPhone 13 iPhone 12 iPhone SE (3rd Generation) iPad mini (5th Generation) iPad Pro (2nd Generation)	iPhone 16 iPhone 15 iPad mini (6th Generation) iPad (10th Generation) iPad Air (4th Generation) iPad Pro (6th Generation)	Ascom Myco 4 Cisco CP860 Google Pixel 7/7a/8/8 Pro HMD Fusion HMD Pulse HMD Skyline Honeywell CT37 Honeywell CT30 (non HC Version with USB-C only) Samsung A14 Samsung A15 5G Samsung Galaxy S25 Ultra Samsung S22 Samsung xCover 6 Pro Spectralink Versity 95XX ‡ Spectralink Versity 96XX ‡ Spectralink Versity 97XX ‡ Zebra ET40 Zebra HC20 Zebra HC50 Zebra TC2x Zebra TC5x
		Operating System	iOS 18 iOS 17 iPadOS 18 iPadOS 17	iOS 18 iOS 17 iPadOS 18 iPadOS 17	Android 9
		Device Connectivity	Lightning	USB-C	USB-C

			Apple Devices with Lightning Port	Apple Devices with USB-C Port	Android Devices
Launchpad	Windows	Device Model	Dell OptiPlex 7020 Micro Form Factor (Intel® Core™ i5 14500T vPro®) HP Elite Mini 800 G9 (Intel® Core™ i5 14500T)	Dell OptiPlex 7020 Micro Form Factor (Intel® Core™ i5 14500T vPro®) HP Elite Mini 800 G9 (Intel® Core™ i5 14500T)	Dell OptiPlex 7020 Micro Form Factor (Intel® Core™ i5 14500T vPro®) HP Elite Mini 800 G9 (Intel® Core™ i5 14500T)
		Operating System	Windows 11	Windows 11	Windows 11
		Configuration	16 GB RAM 256 GB Storage	16 GB RAM 256 GB Storage	16 GB RAM 256 GB Storage
		Network Connectivity	Ethernet (Wired)	Ethernet (Wired)	Ethernet (Wired)
		Device Drivers	Intel USB 3.2.0 eXtensible Host Controller - 1.20 (Microsoft) Intel USB 3.1 eXtensible Host Controller - 1.10 (Microsoft)	Intel USB 3.2.0 eXtensible Host Controller - 1.20 (Microsoft) Intel USB 3.1 eXtensible Host Controller - 1.10 (Microsoft)	Intel USB 3.2.0 eXtensible Host Controller - 1.20 (Microsoft) Intel USB 3.1 eXtensible Host Controller - 1.10 (Microsoft)
		Apple MobileDevice	1784.102.1.2	1784.102.1.2	n/a
	Mac	Device Model	Mac Mini M4 Mac mini M2	Mac Mini M4 Mac mini M2	Mac Mini M4 Mac mini M2
		Operating System	macOS Sequoia (15.4 or higher)	macOS Sequoia (15.4 or higher)	macOS Sequoia (15.4 or higher)
		Configuration	16 GB RAM 256 GB Storage	16 GB RAM 256 GB Storage	16 GB RAM 256 GB Storage
		Network Connectivity	Ethernet (Wired)	Ethernet (Wired)	Ethernet (Wired)
		Apple MobileDevice	1784.101.1	1784.101.1	n/a

			Apple Devices with Lightning Port	Apple Devices with USB-C Port	Android Devices
Smarthub	Bretford	Smarthub Models	10-port PowerSync Pro with Display & IMP-82 Reader for iPhone or iPad mini 20-port PowerSync Pro with Display & IMP-82 Reader for iPhone 10-port PowerSync Pro with Display & IMP-82 Reader for iPad		
		Smarthub Firmware	1.1 (PowerSync Pro 2.5) 2.2.16 (PowerSync Pro 2.0)	1.1 (PowerSync Pro 2.5) 2.2.16 (PowerSync Pro 2.0)	1.1 (PowerSync Pro 2.5) 2.2.16 (PowerSync Pro 2.0)
		Launchpad to Smarthub Connection	USB-C to USB-B (Mac mini M4 front ports only) USB-A to USB-B	USB-C to USB-B (Mac mini M4 front ports only) USB-A to USB-B	USB-C to USB-B (Mac mini M4 front ports only) USB-A to USB-B
		Smarthub to Device Connection	USB-A to Lightning	USB-A to USB-C	USB-A to USB-C
		Proximity Card Reader (if not integrated)	IMP-82	IMP-82	IMP-82
	Datamation	Smarthub Models	8-port Unidock for iPhone (Lightning or USB-C) 16-port Unidock for iPhone (Lightning or USB-C) 24-port Unidock for iPhone (Lightning or USB-C) 8-port Unidock for iPad (Lightning or USB-C) 8-port Unidock for Zebra (7-pin) 16-port Unidock for Zebra (7-pin) *All Unidocks can be ordered with or without an IMP-82 Reader.		
		Smarthub Firmware	Cambronix 1.89.3	Cambronix 1.89.3	Cambronix 1.89.3
		Launchpad to Smarthub Connection	USB-C to USB-B (Mac mini M4 front ports only) USB-A to USB-B	USB-C to USB-B (Mac mini M4 front ports only) USB-A to USB-B	USB-C to USB-B (Mac mini M4 front ports only) USB-A to USB-B
		Smarthub to Device Connection	Lightning	USB-C	USB-C
		Proximity Card Reader (if not integrated)	IMP-82	IMP-82	IMP-82

NOTES:

‡ - Imprivata has been made aware of reports that Spectralink Versity devices may cause damage to Bretford Smart Hub ports. This information is shared for awareness; for questions or guidance on this hardware configuration, contact mobile@imprivata.com.